

# Assembly Instructions for the Mounting Stand Kit and ECE 2000

1. Unpack your mounting stand kit (Figure 1). This kit will include a mounting stand post, base, and four screws.
2. Assemble the mounting stand post to the base using the four screws. A 1/8" hex wrench should be used to install the screws.

*NOTE: The post is offset to the left (Figure 2).*



Figure 1. Mounting Stand Kit



Figure 2. Post Installed on Base

3. Remove the reflector's filler plate by removing the four screws that hold it in place (Figure 3). Place the glass shield on the reflector and reinstall the filler plate with the four screws (Figure 4).

*NOTE: Do not overtighten the screws. Doing so may cause the glass shield to crack.*



Figure 3. Reflector with Filler Plate Removed



Figure 4. Glass Shield Installed

4. Locate the reflector mounting brackets and mounting screws.
5. Install the brackets to the rear of the reflector. Install the two bypass connectors into J4 (PN 41069) and J5 (PN 41068) appropriately (Figure 5).
6. Place the reflector assembly on the mounting stand. Install the fireproof work surface on the stand. (Figure 6)
7. Position the urethane UV shield in front of the reflector.



Figure 5. Reflector Mounting Bracket & Bypass Connectors Installed




Figure 6. Attach Reflector to Mounting Stand

8. Attach the connector cable between the power supply and the back of the reflector (Figure 8).
9. Your mounting stand kit is assembled and ready for use.

**For detailed operating instructions, refer to the ECE Flood Lamp User Guide.**



Figure 8. Connect Power Supply to Reflector



Figure 9. Complete Assembly, Front

**DYMAXEDGE™**  
LISTEN. ENVISION. DELIVER.

In addition to our light-curing equipment, Dymax also offers high-performance adhesives designed to rapidly bond glass, metal, and plastic substrates upon exposure to UV/Visible light and a variety of dispensing equipment. Our products are perfectly matched to work seamlessly with each other, providing design engineers with tools to dramatically improve manufacturing efficiency and reduce costs. Dymax is committed to providing the best chemistry, curing equipment, and dispensing systems that offer customers complete manufacturing solutions for their challenging applications.



© 2013 Dymax Corporation. All rights reserved. All trademarks in this guide, except where noted, are the property of, or used under license by Dymax Corporation, U.S.A.

Please note that most dispensing and curing system applications are unique. Dymax does not warrant the fitness of the product for the intended application. Any warranty applicable to the product, its application and use is strictly limited to that contained in Dymax's standard Conditions of Sale. Dymax recommends that any intended application be evaluated and tested by the user to insure that desired performance criteria are satisfied. Dymax is willing to assist users in their performance testing and evaluation by offering equipment trial rental and leasing programs to assist in such testing and evaluations. Data sheets are available for valve controllers or pressure pots upon request. QS058DA 4/12/2013

**Dymax Corporation**  
860.482.1010  
info@dymax.com  
[www.dymax.com](http://www.dymax.com)

**Dymax Oligomers & Coatings**  
860.626.7006  
oligomers&coatings@dymax.com  
[www.dymax-oc.com](http://www.dymax-oc.com)

**Dymax Europe GmbH**  
+49 (0) 611.962.7900  
info\_de@dymax.com  
[www.dymax.de](http://www.dymax.de)

**Dymax UV Adhesives & Equipment (Shenzhen) Co Ltd**  
+86.755.83485759  
dymaxasia@dymax.com  
[www.dymax.com.cn](http://www.dymax.com.cn)

**Dymax UV Adhesives & Equipment (Shanghai) Co Ltd**  
+86.21.37285759  
dymaxasia@dymax.com  
[www.dymax.com.cn](http://www.dymax.com.cn)

**Dymax Asia (H.K.) Limited**  
+852.2460.7038  
dymaxasia@dymax.com  
[www.dymax.com.cn](http://www.dymax.com.cn)

**Dymax Korea LLC**  
82.2.784.3434  
info@dymax.kr  
[www.dymax.co.kr](http://www.dymax.co.kr)